


BEAM

Welcome Guide


- beBEAM has two LED light color modes, White Light and Candle Light.
- Each color mode has 3 brightness settings to make a total of 6 light settings.

Press the power button to turn ON




beBEAM will turn on in White Light Mode.

White Light Mode




Low Power [1st push]
Medium Power [2nd push]
High Power [3rd push]

Candle Light Mode




Low Power [4th push]
Medium Power [5th push]
High Power [6th push]

Turn OFF




Cycle loops back to beginning at the 7th push. Press the power button and hold for 2 seconds to turn off.


End cap and plug options



The bottom cap can be rotated to adjust the position of the power cable.



If using product while suspended, please insert plug as is.



If beBEAM is floor standing, beBEAM may be connected with L-shaped plug provided in the box.

Accessories



Caution!

- Please use genuine or certified cables.
- Do not use in extreme temperatures.
- Do not allow to become wet.
- Do not subject to excessive mechanical shocks.
- Do not disassemble as some parts may be hazardous.

Product Specifications

Model	B001	Width	3.175cm
Power source	AC100V~240V	Weight	1.3kg
AC adapter	DC24V1.5A	Body	Aluminum (Thickness 1.2mm)
Power consumption	Max 18W / Min 2.0W	Top end cap	ABS
Light source	LED Light	Bottom end cap	ABS+Silicon rubber
Brightness	High 1800lm	Fabric	Polyester (Flame proof)
Modes	White, Candle	Rope	Vinylon
LED life	50,000hrs	Pulg	Type A
Total length	145.8cm		

Customer Support

- 12-month Warranty
If purchased through wallcolor.com or Amazon, please provide your purchase number.

- Customer Support Center

Please access our online customer support center here at the following URL

www.wallcolor.com/support

